

NEWCANDESCENT-LED™

DOUBLE DUTY BALLAST COMPATIBLE T8 LED

WORKS WITH OR WITHOUT THE BALLAST

NC/LED-F32T8-18-BC-4K/5K

FEATURES & SPECIFICATIONS

APPLICATIONS

The Double Duty Ballast Compatible LED T8 Lamp is the ideal choice for old style T12 and T8 Fluorescent Tubes that require frequent changing.

The Double Duty Ballast Compatible lamp works **with** or **without** an existing ballast and doesn't require any additional electrical work. **JUST PLUG AND PLAY & YOU'RE ON YOUR WAY!**

FEATURES

- Aluminum Housing with Integrated Heat Sink
- High Lumen Output 110/125 LM/W
- Rated Life of 50,000 Hours
- Simple Installation
- Amazing Energy Saving
- High Power Factor 0.95
- 82 CRI
- Fluorescent Ballast Compatible
- Internal SMPS that can replace existing Ballast
- Stable lumen output for various brands with different ballast factors
- Works **with** or **without** the ballast



WARRANTY

5 years or 50,000 hours limited warranty against manufacturer defects.

Part #	NC/LED-F32T8-18-BC-4K/5K
Power	18 Watts
Lumens	1980/2250
Lm/w	110/125
Life Span	50,000 Hours
Input Voltage	120-277v
CRI	>82
Base	G13 Bi-Pin
CCT	4000k, 5000k
Equivalent	32wT8, 40wT12
Beam Angle	120 Degrees
Power Factor	>90

47.25" x 1"

DIMENSIONS:



www.NewCandescent-LED.com™

800-282-EPIC (3742) | Fax: 201-343-8300 | Larry@EpicLightBulb.com

11 Leuning Street, South Hackensack NJ 07606